



DAFFUE ELECTRONIC SOLUTIONS cc

Reg.No: 2006/081479/23

VAT No: 4080237938

Physical Office Address:
28 Barkley Avenue
Discovery
Roodepoort
South Africa
1711

Postal Address:
P.O. Box 7034
Ansfrere
1711

Contact Numbers and Details:
Telephone: +27 (0)11 472-7965
Facsimile: 086 575 0345 SA only
e-mail: info@daffuees.co.za
website: www.daffuees.co.za



RFR-WID

Description:

The RFR-WID is 28Bit Code Hopping Remote Receiver with a 34Bit Weigand Identification Output that can be used in conjunction with a Standard Access Controller ([MOD-LOG](#)) to control the access criteria for a specific programmed Remote Transmitter.

Technical Information

- Module Size LxWxH	92mm x 66mm x 28mm
- Weigand and Power Cables Length	0.5m 4-core Cable
- Weight	89g
- Power Supply	9 to 12VDC @180mA(Max) – Polarity and Surge Protected
- Temperature and Humidity	-40 to 70°C with up to 90% Relative Humidity
- RF Receiver	433.92MHz UHF Receiver
- Transmitter Frequency Stability	0.032ppm/°C ² 100ppm year
- Receiver Sensitivity	-95dBm
- Status LED	Yes – Indicating Power and on Reception of Data
- Identification Interface	34Bit Standard SIA Weigand Interface
- Wall or Panel Mounting Clips	Yes
- IP Rating on Transmitters and Receiver	54 – Dust Protected, Splash Proof